



940 Warehouse Shipping Order

X12/V3040/940

Version: 1.0

Company:	Simplot Australia
Publication:	2/1/2023
Notes:	

Table of Contents

940	Warehouse Shipping Order	1
ST	Transaction Set Header	3
W05	Shipping Order Identification	4
0100	Loop Name	5
N1	Name	6
N3	Address Information	8
N9	Reference Number	9
G62	Date/Time	11
NTE	Note/Special Instruction	13
0300	Loop Line Item Detail - Warehouse	14
W01	Line Item Detail - Warehouse	15
G69	Line Item Detail - Description	17
N9	Reference Number	18
0320	Loop Assigned Number	19
LX	Assigned Number	20
N9	Reference Number	21
W76	Total Shipping Order	22
SE	Transaction Set Trailer	23

940 Warehouse Shipping Order

Functional Group=OW

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Warehouse Shipping Order Transaction Set (940) for use within the context of an Electronic Data Interchange (EDI) environment. This transaction set can be used to enable the depositor to advise a warehouse to make a shipment, confirm a shipment, or modify or cancel a previously transmitted shipping order.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	W05	Shipping Order Identification	M	1		N1/020	Must use
LOOP ID - 0100					10		
040	N1	Name	M	1		N1/040	Must use
060	N3	Address Information	O	2		N1/060	Used
090	N9	Reference Number	O	10			Used
110	G62	Date/Time	O	10			Used
120	NTE	Note/Special Instruction	O	20		N1/120	Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - 0300					>1		
020	W01	Line Item Detail - Warehouse	O	1		N2/020	Used
030	G69	Line Item Detail - Description	O	5		N2/030	Used
040	N9	Reference Number	O	200			Used
LOOP ID - 0320					>1	N2/140L	
140	LX	Assigned Number	O	1		N2/140	Used
150	N9	Reference Number	O	>1		N2/150	Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	W76	Total Shipping Order	O	1		N3/010	Used
020	SE	Transaction Set Trailer	M	1			Must use

Notes:

- 1/020 To transmit identifying numbers and other basic data for this transaction set
- 1/040 Used to specify entities for the whole pick slip
- 1/060 Optional free format address information.
This may be called twice for each N101 to allow up to 4 lines of 35 character free format address information.
This is only applicable for N101=ST.
- 1/120 Used to display up to ten lines of order text
- 2/020 To transmit basic and most frequent shipment related line item data elements
- 2/030 Describes the item in free format text
- 2/140L The LX loop conveys serial number data.
- 2/140 Used to show order line text

2/150 Used within LX loop to display Line text

3/010 To specify summary details of total items shipped in terms of quantity, weight and volume

Simplot Note:

Example 940 document:

```

ISA\001      \001      \ZZ\9310081000006 \ZZ\9377779291344 \230201\1215\U\00200\000093650\0\VP\>|
GS\OW\931008100000\937777929134\230201\1215\31655\X\003040|
ST\940\31655|
W05\W\5643862\P7427254.LAU\1610097|
N1\CQ\Simplot Australia|
N1\BT\Bidfood Launceston TAS\91\237925|
N1\SF\Fresh Freight Tasmania (7\91\7F|
N1\CA\Fresh Freight Tasmania Pt\91\102410|
N1\ST\Bidfood Launceston TAS\91\237929|
N3\11 Translink Ave\Tasmania TAS 7212|
N9\WP\1362909|
N9\RU\Blank - Route Code 42/RT|
N9\FN\702|
N9\LO\|
G62\10\230203\11\20|
G62\02\230203\11\20|
G62\BB\230201\11\20|
NTE\OR\Please? acknowledge? P/O? advise? o/stocks|
W01\11\CT\VP\40076\LT|
G69\ED Beans Sliced 6x2kg|
N9\L\1.000|
N9\ZZ\ 1000:000:100:0000-00-00|
W01\24\CT\VP\40199\LT|
G69\ED Brussel Sprouts 6x2kg|
N9\L\2.000|
N9\ZZ\ 1000:002:000:0000-00-00|
W01\12\CT\VP\76008\LT|
G69\CK Chiko Rolls 6x2kg|
N9\L\3.000|
N9\ZZ\ 1000:001:000:0000-00-00|
W01\11\CT\VP\01895\LT|
G69\CC Fish Battered 24x110g|
N9\L\5.000|
N9\ZZ\ 1000:000:100:0000-00-00|
W01\8\CT\VP\07457\LT|
G69\CF FlyCkd Beef Meatballs 5x1kg|
N9\L\6.000|
N9\ZZ\ 1000:000:800:0000-00-00|
W01\12\CT\VP\40009\LT|
G69\ED Peas 6x2kg|
N9\L\7.000|
N9\ZZ\ 1000:001:000:0000-00-00|
W01\12\CT\VP\12475\LT|
G69\ED Chunky Avocado Pulp 8x454g|
N9\L\8.000|
N9\ZZ\ 1000:000:119:0000-00-00|
W01\10\CT\VP\07436\LT|
G69\CF Schnitzel Chicken 23x125g|
N9\L\9.000|
N9\ZZ\ 1000:000:999:0000-00-00|
SE\49\31655|
GE\1\31655|
IEA\1\000093650|

```

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set.

Code List Summary (Total Codes: 236, Included: 1)

Code Name

940 X12.189 Warehouse Shipping Order

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Simplot Note: *Unique number assigned by the originator*

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the invoice transaction set).

W05 Shipping Order Identification

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To transmit identifying numbers and other basic data for this transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
W0501	473	Order Status Code	M	ID	1/1	Must use

Description: Code identifying purpose of transaction set.

Code List Summary (Total Codes: 11, Included: 2)

Code Name

G Changes to Other than Line Items

Simplot Note:

Used by Simplot for Load Change Notification

N Original

Simplot Note:

Used by Simplot for Normal Pick Slip

W0502	285	Depositor Order Number	M	AN	1/22	Must use
-------	-----	------------------------	---	----	------	----------

Description: Identifying number for warehouse shipping order assigned by the depositor.

Simplot Note: *Number for customer order assigned by depositor*

Simplot Order Number (8,0 numeric)

W0503	324	Purchase Order Number	O	AN	1/22	Used
-------	-----	-----------------------	---	----	------	------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser.

Simplot Note: *Customer purchase order number. (25 alphanumeric)*

W0505	474	Master Reference (Link) Number	X	AN	1/22	Used
-------	-----	--------------------------------	---	----	------	------

Description: Reference number assigned by the sender to relate a transaction set to a master transaction. (When associating a group of purchase orders, invoices or other transaction sets, use the master reference (link) number to identify the group and the link sequence number to identify individual transaction sets within the group.)

Simplot Note: *Simplot Shipment Number (8,0 numeric)*

Syntax Rules:

1. P0405 - If either W0504 or W0505 is present, then the other is required.

Loop Name

Pos: 040	Repeat: 10
Mandatory	
Loop: 0100	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
040	N1	Name	M	1		Must use
060	N3	Address Information	O	2		Used
090	N9	Reference Number	O	10		Used
110	G62	Date/Time	O	10		Used
120	NTE	Note/Special Instruction	O	20		Used

N1 Name

Pos: 040	Max: 1
Heading - Mandatory	
Loop: 0100	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/2	Must use

Description: Code identifying an organizational entity, a physical location, or an individual

Simplot Note: *Below are the entities that Simplot can refer to on a pick slip.*

Code List Summary (Total Codes: 687, Included: 5)

Code Name

BT	Bill-to-Party	Simplot Note: <i>Qualifies Simplot customer information</i>
CA	Carrier	Simplot Note: <i>Qualifies Carrier information</i>
CQ	Corporate Office	Simplot Note: <i>Qualifies Simplot information</i>
SF	Ship From	Simplot Note: <i>Qualifies Simplot warehouse information</i>
ST	Ship To	Simplot Note: <i>Qualifies Simplot deliver to customer information</i>

N102	93	Name	X	AN	1/35	Used
------	----	-------------	---	----	------	------

Description: Free-form name.

Simplot Note: *If N101 = BT*

Simplot sell to customer name (35 alpha)

If N101 = CA

Carrier name (35 alpha)

If N101 = CQ

Simplot company name (35 alpha)

If N101 = SF

Simplot warehouse name (35 alpha)

If N101 = ST

Simplot deliver to customer name (35 alpha)

N103	66	Identification Code Qualifier	X	ID	1/2	Used
------	----	--------------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67).

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

Code List Summary (Total Codes: 138, Included: 1)

Code Name

91 Assigned by Seller or Seller's Agent

Description: *If N101 = BT, CA, SF, ST*

Simplot Note:

Number is assigned by Simplot

N104	67	Identification Code	X	AN	2/17	Used
------	----	----------------------------	---	----	------	------

Description: Code identifying a party or other code.

Simplot Note: *If N101 = BT*

Simplot sell to JDE customer number (8,0 numeric)

If N101 = CA

Carrier number (8,0 numeric)

If N101 = SF

Simplot warehouse number (2 character)

If N101 = ST

Simplot ship to JDE number (8,0 numeric)

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 060	Max: 2
Heading - Optional	
Loop: 0100	Elements: 2

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/35	Must use

Description: Address information

Simplot Note: 35 character free format address information

If N101 = ST

Deliver to customer address information

N302	166	Address Information	O	AN	1/35	Used
------	-----	---------------------	---	----	------	------

Description: Address information

Simplot Note: Same as N301

N9 Reference Number

Pos: 090	Max: 10
Heading - Optional	
Loop: 0100	Elements: 3

User Option (Usage): Used

Purpose: To transmit identifying numbers and descriptive information as specified by the reference number qualifier

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
N901	128	Reference Number Qualifier	M	ID	2/2	Must use

Description: Code qualifying the Reference Number.

Code List Summary (Total Codes: 859, Included: 4)

Code Name

FN Forwarder's/Agent's Reference Number

Simplot Note:

Qualifies Simplot Zone number

LO Load Planning Number

Simplot Note:

Qualifies Simplot Load number

RU Route Number

Simplot Note:

Qualifies Simplot route

WP Warehouse Pick Ticket Number

Simplot Note:

Qualifies Simplot Picking Slip Number

N902	127	Reference Number	X	AN	1/30	Used
------	-----	------------------	---	----	------	------

Description: Reference number or identification number as defined for a particular Transaction Set, or as specified by the Reference Number Qualifier.

Simplot Note: *If N901 = FN*

Simplot Zone number (10 alpha)

If N901 = LO

Simplot Load number (15 alpha)

If N901 = RU

Simplot route (10 alpha)

If N901 = WP

Simplot Picking Slip Number (8 alpha)

N903	369	Free-form Description	X	AN	1/45	Used
------	-----	-----------------------	---	----	------	------

Description: Free-form descriptive text.

Simplot Note: *If N901 = RU*

Route description (40 alpha)

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.

G62 Date/Time

Pos: 110	Max: 10
Heading - Optional	
Loop: 0100	Elements: 5

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
G6201	432	Date Qualifier	X	ID	2/2	Used

Description: Code specifying type of date.

Code List Summary (Total Codes: 127, Included: 3)

Code Name

02 Delivery Requested on This Date

Simplot Note:

Simplot delivery date

10 Requested Ship Date/Pick-up Date

Simplot Note:

Simplot dispatch date

BB Transaction Control Date

Simplot Note:

Simplot date that pick slip was entered

G6202	373	Date	X	DT	6/6	Used
-------	-----	------	---	----	-----	------

Description: Date (YYMMDD).

Simplot Note: *Date as defined by G6201*

G6203	176	Time Qualifier	X	ID	1/1	Used
-------	-----	----------------	---	----	-----	------

Description: Code specifying the reported time.

Code List Summary (Total Codes: 36, Included: 1)

Code Name

Z Requested Delivery Time

G6204	337	Time	X	TM	4/8	Used
-------	-----	------	---	----	-----	------

Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

Simplot Note: *If G6201=02*

Requested delivery time (HHMMSS)

G6206	624	Century	O	N0	2/2	Used
-------	-----	---------	---	----	-----	------

Description: The first two characters in the designation of the year (CCYY).

Simplot Note: *Century portion of date in G6202*

Syntax Rules:

1. R0103 - At least one of G6201 or G6203 is required.

2. P0102 - If either G6201 or G6202 is present, then the other is required.
3. P0304 - If either G6203 or G6204 is present, then the other is required.

NTE Note/Special Instruction

Pos: 120	Max: 20
Heading - Optional	
Loop: 0100	Elements: 2

User Option (Usage): Used

Purpose: To transmit information in a free-form format, if necessary, for comment or special instruction

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
NTE01	363	Note Reference Code	O	ID	3/3	Used

Description: Code identifying the functional area or purpose for which the note applies.

Code List Summary (Total Codes: 57, Included: 1)

Code Name

ORI Order Instructions

NTE02	3	Free Form Message	M	AN	1/60	Must use
-------	---	--------------------------	---	----	------	----------

Description: Free-form text.

Simplot Note: *Order text (60 alpha)*

Comments:

1. The NTE segment permits free-form information/data which, under ANSI X12 standard implementations, is not machine processable. The use of the ``NTE" segment should therefore be avoided, if at all possible, in an automated environment.

Loop Line Item Detail - Warehouse

Pos: 020	Repeat: >1
Optional	
Loop: 0300	Elements: N/A

User Option (Usage): Used

Purpose: To transmit basic and most frequent shipment related line item data elements

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
020	W01	Line Item Detail - Warehouse	O	1		Used
030	G69	Line Item Detail - Description	O	5		Used
040	N9	Reference Number	O	200		Used

W01 Line Item Detail - Warehouse

Pos: 020	Max: 1
Detail - Optional	
Loop: 0300	Elements: 6

User Option (Usage): Used

Purpose: To transmit basic and most frequent shipment related line item data elements

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
W0101	330	Quantity Ordered	M	R	1/9	Must use

Description: Quantity ordered.

Simplot Note: Allocated quantity (8,0 numeric)

W0102	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

Code List Summary (Total Codes: 719, Included: 3)

Code Name

CT Carton

EA Each

KG Kilogram

Simplot Note:

Simplot expect the 940 Pick Slip W0102 element UOM sent to the 3PL to be matched by the 945 Pick Slip Confirmation (element W1205 in segment W12)

W0104	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234).

Code List Summary (Total Codes: 307, Included: 1)

Code Name

VP Vendor's (Seller's) Part Number

W0105	234	Product/Service ID	X	AN	1/30	Used
-------	-----	--------------------	---	----	------	------

Description: Identifying number for a product or service.

Simplot Note: *Simplot JDE product number (15 alpha)*

W0106	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234).

Code List Summary (Total Codes: 307, Included: 1)

Code Name

LT Lot Number

W0107	234	Product/Service ID	X	AN	1/30	Used
-------	-----	--------------------	---	----	------	------

Description: Identifying number for a product or service.

Simplot Note: *Simplot Lot ID. (10 alpha)*

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		<i>This is usually a manufacture or use-by date in DDMMYY format.</i>				

Syntax Rules:

1. R0304 - At least one of W0103 or W0104 is required.
2. P0405 - If either W0104 or W0105 is present, then the other is required.
3. P0607 - If either W0106 or W0107 is present, then the other is required.

G69 Line Item Detail - Description

Pos: 030	Max: 5
Detail - Optional	
Loop: 0300	Elements: 1

User Option (Usage): Used

Purpose: To describe an item in free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
G6901	369	Free-form Description	M	AN	1/45	Must use

Description: Free-form descriptive text.

Simplot Note: *Product description (30 alpha)*

N9 Reference Number

Pos: 040	Max: 200
Detail - Optional	
Loop: 0300	Elements: 3

User Option (Usage): Used

Purpose: To transmit identifying numbers and descriptive information as specified by the reference number qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Number Qualifier	M	ID	2/2	Must use

Description: Code qualifying the Reference Number.

Code List Summary (Total Codes: 859, Included: 2)

Code Name

- LI Line Item Identifier (Seller's)
- ZZ Mutually Defined

N902	127	Reference Number	X	AN	1/30	Used
------	-----	------------------	---	----	------	------

Description: Reference number or identification number as defined for a particular Transaction Set, or as specified by the Reference Number Qualifier.

Simplot Note: *If N901 = LI*

Simplot order line number (6,3 numeric)

If N901 = ZZ

Refer 5.15.2.2 for lot status codes (3 Alpha) or blank

N903	369	Free-form Description	X	AN	1/45	Used
------	-----	-----------------------	---	----	------	------

Description: Free-form descriptive text.

Simplot Note: *If N901 = ZZ*

Pallets/layer/cartons/best before date

Best before date format = yyyy-mm-dd

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.

Loop Assigned Number

Pos: 140	Repeat: >1
Optional	
Loop: 0320	Elements: N/A

User Option (Usage): Used

Purpose: To reference a line number in a transaction set.

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
140	LX	Assigned Number	O	1		Used
150	N9	Reference Number	O	>1		Used

LX Assigned Number

Pos: 140	Max: 1
Detail - Optional	
Loop: 0320	Elements: 1

User Option (Usage): Used

Purpose: To reference a line number in a transaction set.

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
LX01	554	Assigned Number	M	N0	1/6	Must use

Description: Number assigned for differentiation within a transaction set.

Simplot Note: *Order line text sequence number (6,3 numeric)*

N9 Reference Number

Pos: 150	Max: >1
Detail - Optional	
Loop: 0320	Elements: 2

User Option (Usage): Used

Purpose: To transmit identifying numbers and descriptive information as specified by the reference number qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Number Qualifier	M	ID	2/2	Must use

Description: Code qualifying the Reference Number.

Code List Summary (Total Codes: 859, Included: 1)

Code Name

ZZ Mutually Defined

N903	369	Free-form Description	X	AN	1/45	Used
------	-----	-----------------------	---	----	------	------

Description: Free-form descriptive text.

Simplot Note: *Simplot line item text (45 alpha)*

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.

W76 Total Shipping Order

Pos: 010	Max: 1
Summary - Optional	
Loop: N/A	Elements: 1

User Option (Usage): Used

Purpose: To specify summary details of total items shipped in terms of quantity, weight, and volume

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
W7601	330	Quantity Ordered	M	R	1/9	Must use

Description: Quantity ordered.

Simplot Note: *Total number of cartons ordered*

Syntax Rules:

1. P0203 - If either W7602 or W7603 is present, then the other is required.
2. P0405 - If either W7604 or W7605 is present, then the other is required.
3. C0603 - If W7606 is present, then W7603 is required.

Comments:

1. Equivalent weight is given in the same unit of measure as weight.
2. Quantity ordered (W7601) is a "Hash" total and the unit of measure is not required.

SE Transaction Set Trailer

Pos: 020	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments).

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use

Description: Total number of segments included in a transaction set including ST and SE segments.

Simplot Note: *Usually generated by EDI software*

SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Simplot Note: *Same number as ST02*

Comments:

- SE is the last segment of each transaction set.